

XW Pro

6.8/8.5 kW hybrid inverter/chargers for North America

865-6848-21



The ultimate backup power and off-grid performance for solar & storage systems. The XW Pro is the evolution of Schneider Electric's two decades of experience in highly reliable solar & storage off-grid and backup power systems, with the scalability and flexibility to meet your system requirements.

Backup power and off-grid performance

- Reliable operation of backup power and off-grid loads with a high overload power rating (1.75x)
- Seamless transition to backup power with an integrated high-speed transfer switch
- Grid and Generator input ports
- Field proven product quality and reliability

Flexible

- 120/240 V output with stacking capability up to 4 units
- Integrates with Conext™ MPPT Charge Controllers as well as grid tied PV inverters for DC-coupled or AC-coupled systems
- Lithium Ion battery integration
- Grid tied and off-grid systems, Rule 21, HECO Rule 14H and PREPA compliant

Easy to Install

- Configures quickly using the Conext Gateway and Insight
- AC Out port for backloads
- Full ecosystem and accessories for single unit or scalable systems

solar.schneider-electric.com

Smart Energy Management

- Optimize energy consumption for time of use rates or demand charges
- Self-consumption of solar energy

Compatible with Gateway & Insight 2

- Remote monitoring & control with advanced data security
- Web and mobile app
- Multi-site management for installers

*Please note that Conext Gateway is required for the commissioning of the XW Pro.



Technical Specifications

XW Pro 6848 NA	
Inverter AC Output (Standalone)	
Output power (continuous) at 25°C	6800 W
Overload 30 min/60 sec at 25°C	8500 W/12000 W
Output power (continuous) at 40°C	6000 W
Maximum output current 60 seconds (rms)	52 A (240 V)
Output frequency	50/60 Hz
Output voltage	Split phase 120/240 V +/- 3%
Total harmonic distortion at rated power	< 5 %
Idle consumption search mode	< 8 W
Input DC voltage range	40 to 64 V (48 V nominal)
Maximum input DC current	180 A
Charger DC Output	
Maximum output charge current	140 A
Output charge voltage range	40 – 64 V (48 V nominal)
Charge control	Three stage, two stage, boost, external BMS, custom
Charge temperature compensation	Battery temperature sensor included
Power factor corrected charging	0.98
Compatible battery types	Flooded (default), Gel, AGM, Lithium ion, custom
Battery bank range	440 – 10000 Ah
AC Input	
AC 1 (grid) input current (selectable limit)	3 – 60 A (60 A default)
AC 2 (generator) input current (selectable limit)	3 – 60 A (60 A default)
Automatic transfer relay rating/typical transfer time	60 A / 8 ms
AC input voltage limits (bypass/charge mode)	L-L: 156 - 280 V (240 V nominal)
AC input frequency range (bypass/charge mode)	52 – 68 Hz (allowable)
AC Grid-Tie Output	
Grid sell power	6000 W
Grid sell current (selectable limit)	0 to 27 A (240 V)
Efficiency	
Peak	95.1%
CEC weighted efficiency	93.0%
General Specifications	
Part number	865-6848-21
Product/shipping weight	55.2 kg (121.7 lb)/76.7 kg (169.0 lb)
Product dimensions (H x W x D)	58 x 41 x 23 cm (23 x 16 x 9 in)
Shipping dimensions (H x W x D)	71.1 x 57.2 x 39.4 cm (28.0 x 22.5 x 15.5 in)
IP degree of protection	NEMA Type 1 Indoor
Operating air temperature range	-25°C to 70°C (-13°F to 158°F) (power derated above 25°C (77°F))
Features	
System monitoring and network communications	Available (through Conext™ Gateway)
Intelligent features	Grid sell, peak load shave, generator support, solar self-supply
Auxiliary port	0 to 12 V, maximum 250 mA DC output, selectable triggers
Off-grid AC coupling	Frequency shifting
Regulatory Approval	
Safety	UL1741, CSA 107.1
EMC directive	FCC and Industry Canada Class B
Interconnect	IEEE 1547, UL 1741-SA, Rule 21, Rule 14H, PREPA, and CSA 107.1
Compatible Products Part Numbers	
Power Distribution Panels	XW Mini PDP (865-1013-01), XW PDP (865-1015-01)
MPPT Charge Controllers	MPPT 100 600 (865-1034), MPPT 80 600 (865-1032), MPPT 60 150 (865-1030-1)
Monitoring	Gateway (865-0329), Insight 2
Accessories	System Control Panel (865-1050), Automatic Generator Start (865-1060), Battery Monitor (865-1080-01), Configuration Tool (865-1155-01)